

Q.brixx X station B | EC

EtherCAT add-on for Q.station-X

Q.station X is a high-performance edge controller for data acquisition, which provides accurate synchronization of measurement data, high-speed redundant data logging, and parallel communication over TCP/IP, CAN, ProfiNET, Modbus, and EtherCAT. The Q.station X comes with an optional full-featured programmable application controller designed for complex control and automation tasks.

- High density and flexibility with 16 modules in one system in any constellation
- Electromagnetic Compatibility according to EN61000-4 and EN55011
- Connectable to Controller Q.station
- Power supply 10 ... 30 VDC

Key Features

- EtherCAT extension based on Ethernet standard



Q.brixx X station B | EC

EtherCAT add-on for Q.station-X

Technical Data

Requires Q.series-X Controller: Q.station-X

This product consists of the Q.station-X controller with the extension as specified in this datasheet..

You can find the datasheet for the Q.station-X controller on the Gantner Instruments website.

All specifications and facts of the Q.station-X datasheet, if not stated otherwise, also apply to this device.

EC Specifications

Electrical standard	Ethernet
Data storage	1024 Byte Data (253 variables read and 253 variables write)
Baud rate	100 Mbps
Cycle time	≥100 μs
isolation voltage	500 V

Mechanical information

Material	Aluminum
Measurements (W x H x D)	60x 137 x 135mm
Weight	approx. 700 g

Ordering Information

Article number	584631
----------------	--------

Gantner Instruments

Austria | Germany | France | Sweden | India | USA | China | Singapore
Montafonerstraße 4 · A-6780 Schruns · T +43 55 56 · 77 463-0

office@gantner-instruments.com
www.gantner-instruments.com